


feelspo^ot

Smart Switch Instruction

Parameters

- Product: Smart Breaker
- Rated Voltage: AC 90-250V
- Rated Current:10A(Max.)
- AC Frequency:50-60Hz
- Max.Power: 2200W for 220V, 1100W for 110V

Installation method



The power must be disconnected, pay attention to safety

Part1:Download & Registration

- Scan the QR code to download " SmartLife " app from APP Store or Google Play.
- Enter the register/login interface, input the phone number for getting verification code to register or through other methods at the bottom of page connecting to related authorization interface to log in.
- Note: Our APP only supports 2.4GHz Wi-Fi network



Part2:Easy Mode(Recommend)

Preparation:Device has connected with electricity, long press on/off button for 5 seconds until indicator light quickly flashes,the application already stepped into " Devices" interface.

- Phone has connected to WiFi router and been able to connected to Internet.
- Tap the icon "+" at the top right corner of "Devices"
- Make sure the indicator light is flashing quickly, then tap the related button in application.
- Choose the local WiFi and enter the correct password, tap "Next".
- Wait for configuring successfully, then tap "Done"

Part3:AP Mode

If failed in EZ mode, automatically skip to AP mode, or tap the icon "+" at the top right corner of "Devices", enter into "Add Device", tap "AP mode" at the top right corner.

- Long press on/off button until indicator light slowly flashes, then tap the related button in application, enter into another interface, tap "Next".
- Tap "Connect now", choose WiFi hotspot named "SmartLife-XXXX", then back to "SmartLife " application
- Wait for configuring successfully, then tap "Done".
- Users could rename the device through tapping the icon in the middle of interface.

Part4:Profile

Profile is the entrance for the users to manage personal information, mainly show the following information (see chart):



Notice

- Please check if there is damage caused by transportation, if yes, please contact supplier for replacement.
- Please follow the specification instruction and notice to keep products in a good and safe use condition.
- Put the Smart breaker in proper condition and out of reach of the children.
- Plug in fully to the socket while using.
- The total power of being electric connected appliances could not be bigger than the maximum power of the socket.
- Do Smart breaker disassemble or install the socket, otherwise there may cause security risks.

Using Amazon Echo Quick Guide

Preparation

- Amazon Alexa APP
- Amazon Alexa account (users need to register their own account)
- Our Smart APP
- Our Smart APP account (users need to register their own account, select region as "The United States")
- Echo, Echo Dot ,Tap and other Amazon voice-operated devices
- Our smart device (for example, Smart Socket)

Rename the device after configuring successfully. The name of the device is recommended to use easy pronunciation of the English words.

Set your Echo speaker by Alexa APP

- Sign in with Alexa account & password. (If not registered, sign up first.) After login, click the menu at the top left, then click "Settings", and choose "Set up a new device".
- Choose a device (for example, Echo). When the right page appears, long press the small dot on your Echo device until the light turns to be yellow. Then click "Continue" on App. (Note: at this time the mobile phone can not open a variety of VPN software)



- Choose users' wifi and wait for a few minutes.
- After an introduction video, click next step, it will go to "Home" page automatically. Now the Echo is connected to Alexa APP through WiFi successfully.

Enable Our Skill in Alexa APP

- Choose "Skills" in the options bar, and then search " SmartLife " in the input box. Select " SmartLife " in the search results, and then click "Enable Skill". (Note: If there are more than one test, there will be the interface on the right, which indicates that the account has been bound. You can click on the "Disabel Skill" to remove the binding, and then click on the "Enable Skill" to continue to bind a new SmartLife account.)

- Input the user name and password that you had previously registered (Only support the account in the United States); When you see the right page, it means the Alexa account is linked with SmartLife account.



Enable Our Skill in Alexa APP

After the previous operation is successful, you can control the socket via Echo.

- Discover devices : Firstly, users need to say to Echo: "Echo (or Alexa), Discover my devices." Echo will start to find the devices which is added in SmartLife APP, it will take about 20 seconds to show the result. Or click "Discover devices" in Alexa APP, it will show the devices that found successfully.



Note: "Echo" is one of the wake-up name, which can be any of these three names (Settings): Alexa/Echo/Amazon

- Support Skill List
User can control devices by instructions like below:
Alexa, turn on [bedroom socket]
Alexa, turn off [bedroom socket]

Note: The name of the device must be consistent with the addition of SmartLife app.

Disposal:
Dispose of the device over a registered waste disposal firm or through your communal waste disposal facility. Observe the currently valid regulations. In case of doubt, consult your waste disposal facility.

Warranty:

30 days free replacement: any defective product can be replaced or repaired within the 30 days of purchase. The customer can choose between free replacement and free repair. If the customer asks for free replacement, he can only ask for the same version of the product bought, and if that version is no longer available, we'll replace it with another product of the same brand with similar or better performances. 1 years free maintenance: free maintenance within 1 years of purchase, if the product is found to be defective under

